



multiload

LEDrose LDR100

0/1-10V controlled dimming driver
for constant current LEDs

Contents

| | |
|--|----------|
| Overview and technical specification | |
| LDR100-L | 2 |
| LDR100-H | 3 |
| Installation – general | 4 |
| Installation – set-up | 5 |
| Multiload product options | 6 |
| Wiring diagrams | |
| Rotary Push-switch Wall Dimmer RPS | 6 |
| Rotary Push-switch Wall Dimmer RPC | 7 |
| Rotary Push-switch Wall Dimmer RPC and Lighting Contactor LC100 | 7 |
| Take Control | 8 |
| Take Control and Lighting Contactor LC100 | 8 |
| MoodMaker Scene-setting System | 9 |

Product order codes

LDR100-L

Ten different maximum current settings selectable by user between 100mA and 750mA.

LDR100-H

Ten different maximum current settings selectable by user between 500mA and 1400mA.

Factory-set

LEDrose LDR100 can be supplied with the current factory-set to customer requirement between 100mA and 1400mA.



Overview – LDR100-L (100mA–750mA)

LEDRose LDR100-L uses Constant Current Reduction (CCR) technology to provide smooth consistent flicker-free dimming to zero of constant current LED lamps or strips.


Can be positioned at great distances from the LED light source(s), allowing placement in electrical distribution cupboards or other convenient locations.

Maximum output current between 100mA and 750mA.


LDR100-L supplied with 10 maximum current settings on a multi-position switch, selectable between 100mA and 750mA. (See multi-position switch table).

Features

- Output maximum current range 100mA to 750mA.
- Smooth flicker-free light level adjustment down to 0.0001% with 0/1-10V control.
- DALI and DMX interfaces available.
- Hot pluggable (allowing LEDs to be replaced without switching off the power).
- Short circuit protected.
- Can be placed hundreds of metres from LEDs.
- CCR (Constant Current Reduction) dimming keeps RFI along the cabling to a minimum (because current is not constantly switched on/off as in PWM dimming).
- Monitoring of current settings over time, allowing warranties to be honoured.
- Class 2 product requires power supply to applicable national standard.
- Any number of LEDRose LDR100-Ls can be connected, up to 50% of the rating of the power supply, provided it can maintain the 15V supply under all conditions.
- Compatible with control products from other manufacturers



LDR100-L output current settings



Multi-position switch table

| Position | Function | max current |
|----------|----------------|-------------|
| 0 | Initial set-up | |
| 1 | Operation | 100mA |
| 2 | Operation | 200mA |
| 3 | Operation | 250mA |
| 4 | Operation | 300mA |
| 5 | Operation | 350mA |
| 6 | Operation | 400mA |
| 7 | Operation | 500mA |
| 8 | Operation | 600mA |
| 9 | Operation | 700mA |
| A | Operation | 750mA |

Technical information

Mechanical

DIN-rail mounted unit supplied with 3 standalone brackets.

Supply input voltage (15V)

15V ± 10% DC. Any number of LEDRose LDR100-Ls can be connected, up to 50% of the wattage of the power supply.

Output forward voltage

3V – 45V

Maximum output current

LDR100-L: Adjustable using positions 1-A on the multi-position switch between 100mA and 750mA.

Control input

0/1-10V signal.

DALI and DMX interfaces available

Monitoring

Time operated at different maximum currents is recorded

Efficiency

LEDRose LDR100-L is greater than 90% efficient under maximum load.

Environment / humidity

Maximum 90% rh non-condensing

Ambient temperature range

-10°C – 40°C

Terminals

High quality rising clamp, allows easy connection, accepts stranded cable up to 4mm²

Physical data

Weight: 270g

Finish: Plastic

Dimensions: W:88mm D:90mm H:58mm



Overview – LDR100-H (500mA–1400mA)

LEDrose LDR100-H uses Constant Current Reduction (CCR) technology to provide smooth consistent flicker-free dimming to zero of constant current LED lamps or strips.

Can be positioned at great distances from the LED light source(s), allowing placement in electrical distribution cupboards or other convenient locations.

Maximum output current between 500mA and 1400mA.


LDR100-H supplied with 10 maximum current settings on a multi-position switch, selectable between 500mA and 1400mA. (See multi-position switch table).

Features

- Output maximum current range 500mA to 1400mA.
- Smooth flicker-free light level adjustment down to 0.0001% with 0/1-10V control.
- DALI and DMX interfaces available.
- Hot pluggable (allowing LEDs to be replaced without switching off the power).
- Short circuit protected.
- Can be placed hundreds of metres from LEDs.
- CCR (Constant Current Reduction) dimming keeps RFI along the cabling to a minimum (because current is not constantly switched on/off as in PWM dimming).
- Monitoring of current settings over time, allowing warranties to be honoured.
- Class 2 product requires power supply to applicable national standard.
- Any number of LEDrose LDR100-Hs can be connected, up to 50% of the rating of the power supply, provided it can maintain the 15V supply under all conditions.



LDR10-H output current settings



Multi-position switch table

| Position | Function | max current |
|----------|-----------|-------------|
| 1 | Operation | 500mA |
| 2 | Operation | 600mA |
| 3 | Operation | 700mA |
| 4 | Operation | 750mA |
| 5 | Operation | 800mA |
| 6 | Operation | 900mA |
| 7 | Operation | 1000mA |
| 8 | Operation | 1050mA |
| 9 | Operation | 1200mA |
| A | Operation | 1400mA |

Technical information

Mechanical

DIN-rail mounted unit supplied with 3 standalone brackets.

Supply input voltage (15V)

15V ± 10% DC. Any number of LEDrose LDR100-Hs can be connected, up to 50% of the wattage of the power supply.

Output forward voltage

3V – 45V

Maximum output current

LDR100-H: Adjustable using positions 1-A on the multi-position switch between 500mA and 1400mA.

Control input

0/1-10V signal.

DALI and DMX interfaces available

Monitoring

Time operated at different maximum currents is recorded

Efficiency

LEDrose LDR100-H is greater than 90% efficient under maximum load.

Environment / humidity

Maximum 90% rh non-condensing

Ambient temperature range

-10°C – 40°C

Terminals

High quality rising clamp, allows easy connection, accepts stranded cable up to 4mm²

Physical data

Weight: 270g

Finish: Plastic

Dimensions: W:88mm D:90mm H:58mm



Installation – general

LEDrose LDR100


- Installation should be carried out by suitably qualified personnel in accordance with good wiring practice and the appropriate national wiring regulations.
- Only a single 2-core cable or a single feed and return cable are required for wiring LDR100 to the LED(s)
- Remote positioning eliminates the need to locate drivers in the ceiling or run mains and dimming signal wiring
- Minimised maintenance: LEDrose LDR100s can be placed in any suitable location to make access easy
- The LEDrose is SELV compatible. If SELV status is required for the installation the power supply and the dimming signal must also be SELV compatible (please check with controls manufacturer to ensure the dimming signal is also SELV).

Series connection and maximum voltage

Each LED requires a certain voltage when running at its nominal current; (this nominal voltage is calculated by dividing nominal power by nominal current, eg. a 14W lamp at 700mA requires $14W \div 0.7A = 20V$).

When connected in series the total nominal voltage (plus any cable volt drop) connected to LEDrose LDR100 must not exceed 45V, the voltage capability of the output.

Series connection




Power supply and series wiring diagrams

LEDrose LDR100 with one individual LED lamp.
 1 x 10W 300mA.
 Nominal voltage:
 $10 \div 0.3 \approx 33V$

LEDrose LDR100 with two lamps wired in series.
 2 x 14W 700mA.
 Nominal voltage:
 $(2 \times 14) \div 0.7 \approx 40V$

LEDrose LDR100 with five lamps wired in series.
 5 x 6W 700mA.
 Nominal voltage:
 $(5 \times 6) \div 0.7 \approx 43V$





Installation – set-up

LEDrose LDR100-L and LDR100-H

User-set using one of ten maximum current settings on multi-position switch (see tableS on previous pages).

Preparation

Before switching on supply:

- Connect LED(s) to output terminals. If cabling a string of LED lamps these must be series wired (see page 4), with a combined nominal voltage $\leq 45V$.
- Connect 15V power supply and 0/1-10V control signal to input terminals.
- Adjust multi-position switch to position 0.
- Ensure lamp or series of lamps are connected.

Set-up

- Switch on supply and wait between 30 seconds to one minute. The unit will calculate the correct forward voltage between 3V and 45V for the LED or string of LEDs. The lamp(s) will reach a steady state brightness level, it will then switch itself off and within a couple of seconds re-establish a brightness level commensurate with the 0/1-10V signal input.
- Switch off supply and adjust the multi-position switch to whatever current is required (see tables on pages 2 and 3).
- Switch on supply and adjust the 0/1-10V input signal to maximum for one minute.
- The unit will then now be fully operational and set a brightness level commensurate with the 0/1-10V signal input.

To change to new lamp type

If a different output current or lamp voltage is to be used the preparation and set-up process described above is required to reset LDR100.

If a short circuit is detected

When the LDR100 detects a short circuit on the output it will shut down and a power reset is required to restart the LDR100 (switch power off, wait a few seconds and switch power on again)

To review driver monitor


To review stored usage history of driver please contact supplier.

Factory set option


Can be supplied with maximum current factory-set on a particular switch position to customer requirement between 100mA and 1400mA.



LEDrose LDR100 with Multiload product options




LEDrose LDR100 wired to Rotary Push-switch Wall Dimmer RPS






LEDrose LDR100 wired to Rotary Push-control Wall Dimmer RPC




LEDrose LDR100 wired to Rotary Push-control Wall Dimmer RPC and Lighting Contactor LC100T






LEDrose LDR100 wired to Take Control Unit TCU



DRAWING NOT TO SCALE
WD-LDR100-TCU. ISS-2-0117


LEDrose LDR100 wired to Take Control Unit and Lighting Contactor LC100



DRAWING NOT TO SCALE
WD-LDR100-TCU-LC. ISS-2-0117



LEDrose LDR100 wired to MoodMaker Set-up Unit MMSU



DRAWING NOT TO SCALE
WD-LDR100-MMSU. ISS-2-0117